

Digitus® Univerzalni adapter za utičnicu s 2 x USB-A priključka

DA-70617

EAN 4016032458913



Power Adapter with 2 USB Ports 250V, 50 Hz, USB: 5V, 2.1A, white/grey

Praktično punite svoje mobilne uređaje poput pametnih telefona ili tableta na bilo kojoj električnoj utičnici. Integrirana sigurnosna utičnica omogućuje vam da i dalje koristite postojeću utičnicu, a istovremeno možete koristiti i dvije USB-A utičnice za punjenje. Male dimenzije također čine utični punjač idealnim suputnikom na putovanjima. Zaštitite sebe i svoju obitelj od električnog udara pomoću integriranih zaštitnih poklopaca i povećane zaštite od dodira sigurnosnih utičnica. Osim toga, utičnica nudi zaštitu od kratkog spoja i preopterećenja, sprječavajući oštećenje priključenih mobilnih uređaja i kućanskih aparata. Plug & Play – samo ga priključite i počnite koristiti.

Punite dva mobilna uređaja istovremeno bez gubitka sigurnosne utičnice

- LED indikator funkcije za USB utičnice za punjenje
- Zaštita od dodira: Plastične kapice brtve kontakte utičnice

- Integrirana zaštita od kratkog spoja
- Integrirana zaštita od preopterećenja
- 1 x sigurnosna utičnica: 250 V / 50 Hz, 16 A - 3680 W max.
- 2 x USB-A priključka (ukupno 5V / 2.4A)
- Napon mreže: 250 V / 50 Hz, 16 A
- Razred zaštite: IP 20
- Težina: 105 g
- Dimenzije: D 10 x Š 5,2 x V 7,3 cm

Attributes

- Vrsta: Punjač/napajanje

Package contents

- 1 x univerzalni USB punjač sa 2 x USB-A utičnice i integriranom električnom utičnicom
- 1 x QIG

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	100	15.00	44.00	42.00	35.00	64,680.00
Packaging Unit Inside	1	0.15	6.00	8.00	10.50	504.00
Packaging Unit Single	1	0.15	6.00	8.00	10.50	504.00
Net single without Packaging	1	0.10	5.20	7.30	10.30	0.00

More images:



Safety notes

- Use charging adapters or power supply units in accordance with the instructions in the operating instructions to ensure optimum performance.
- Connect the charging adapter to an easily accessible socket in the voltage range between 100-240 V AC.
- Disconnect the charging adapter from the socket after use.
- Do not use the charging adapter with electronic devices that are outside the specifications of the charging adapter.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schöffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com