

DIGITUS® Conjunto de baterias externas da UPS para modelos de UPS de 6kVA e 10kVA (módulo de expansão)

DN-170108

EAN 4016032473596



Módulo de bateria com bateria interna (20 unidades)

Os módulos de bateria da UPS DIGITUS® asseguram que os sistemas UPS utilizados em ambientes altamente exigentes continuem a fornecer, de forma fiável, energia aos dispositivos ligados em caso de interrupções de fornecimento. É possível ligar um máximo de 4 módulos de bateria para aumentar o tempo de funcionamento dos dispositivos de TI ligados. Isto assegura que os sistemas estão protegidos com uma fonte de alimentação ininterrupta durante as mudanças de bateria. Os conjuntos de baterias externos podem aumentar rapidamente o tempo de ponte à medida que a procura aumenta.

Uma solução que aumenta a capacidade operacional dos sistemas UPS inteligentes para proteger dispositivos de TI com cargas médias a elevadas

- O módulo de bateria pode ser instalado num bastidor de 19" ou como uma torre com um suporte
- Troca a quente - a bateria pode ser substituída durante o funcionamento
- Compatível com as UPS OnLine: DN-170106 & DN-170107
- Tensão da bateria: ±120 VDC
- Capacidade (unidade padrão): 12 V / 9 Ah
- Número de pilhas incorporadas: 20

- Baterias em série: 10 (por módulo de bateria)
- Tipo de bateria: Bateria de chumbo-ácido
- Tempo de carregamento típico: 6 a 8 horas para restaurar 90% da capacidade total
- Temperatura de funcionamento: 20°C a 25°C
- Humidade durante o funcionamento: 0 - 90 %
- Ligações dos terminais traseiros
- Dimensões (C×L×P): 131 x 443 mm x 680 mm
- Peso líquido: 65 kg
- Peso bruto : 66 kg

Attributes



- Installation: Rack OU, Rack 1U
- Installation: Rack
- Power: 6000VA - 10000VA
- Technology: Online double conversion
- Inch form factor (IEC 60297): 482.6 mm (19")

Package contents

- 1 x conjunto de baterias externas da UPS para os modelos de UPS de 6kVA e 10kVA (módulo de expansão)
- 1 x manual de instruções
- 1 x cabo de ligação (para ligar a UPS e o módulo de bateria), 1,5 m

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	1	68.20	77.20	56.50	26.50	115,588.00
Packaging Unit Inside	1	68.20	0.00	0.00	0.00	0.00
Packaging Unit Single	1	68.20	73.00	58.50	28.00	119,574.00
Net single without Packaging	1	65.00	68.00	44.30	13.10	0.00

More images:



Safety notes

- The UPS system must be absolutely dry before it is installed. Please allow the UPS system to acclimatize for at least two hours to adapt to the environment.
- Protect the UPS system from water or moisture.
- Avoid direct sunlight or installation near heat sources.
- Do not block any ventilation openings in the housing.
- Do not connect any devices or appliances that would overload the system.
- Lay cables so that nobody can step on them or trip over them.
- Do not connect any household appliances to the output sockets of the UPS system.
- Only connect the UPS system to an earthed and easily accessible socket.
- Only use VDE-tested, CE-marked mains connection cables at the input and outputs.
- Never disconnect the mains connection cable during operation as this would cancel the protective earthing of the UPS system and all connected loads.
- The UPS system has its own internal power source. The output sockets or output terminals of the UPS system can be energized even if the UPS system is not connected to the building cabling.
- To switch off the UPS system completely, first press the OFF/Enter button to disconnect the mains.
- Caution - Risk of electric shock. Even after disconnecting the device from the mains, the components inside the UPS system are still connected to the battery. There is a risk of electric shock.
- Only persons who are sufficiently familiar with batteries and the necessary safety precautions may replace batteries and monitor operation.
- Caution - Risk of electric shock. The battery circuit is not isolated from the input voltage. Dangerous voltages can occur between the battery terminals and the ground. Ensure that no voltage is present before touching!
- When replacing the batteries, install the same number and type of batteries.
- Do not open or destroy batteries. Leaking electrolyte can injure the skin and eyes and may be toxic.
- The appliance may only be opened and repaired by a trained specialist.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com