

# DIGITUS® Kit de montagem de UPS para armários de rede/servidores de 19" (calha de perfil)

DN-170109

EAN 4016032473619



### Kit de calhas para UPS 1K-10K (2U ou 3U) com embalagem

Com este kit de montagem, os sistemas UPS podem ser instalados em armários de rede ou de servidores DIGITUS® de 483 mm (19"). Podem ser instaladas fontes de alimentação de emergência com 2 ou 3 U de altura, compatíveis com os sistemas UPS DIGITUS® OnLine (1K-10K). A instalação é efectuada em 4 calhas de perfil do bastidor de 19".

### O kit de montagem permite uma instalação fácil dos sistemas UPS OnLine em armários de rede/servidores de 19"

- Para instalação fixa nas quatro calhas de perfil de 483 mm (19")
- 1 peça é composta por duas partes (sistema de perfis interno e externo)
- Variável para as seguintes profundidades: 468,5 mm a 1000 mm
- Incl. material de montagem

- Dimensões (C×L×P): 85 x 65 mm x 496,5 mm
- Peso líquido: 2,77 kg
- Peso bruto : 3,37 kg
- Cor: Prateado

### Attributes

- Color: light grey, RAL 7035
- Installation: Rack
- Units: 2
- Inch form factor (IEC 60297): 482.6 mm (19")

### Package contents

- 1 x kit de montagem da UPS para armários de rede/servidores de 19"
- 1 x guia de instalação

### Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	8	27.50	59.50	21.70	21.00	27,114.20
Packaging Unit Inside	1	3.44	48.80	9.50	4.70	2,178.92
Packaging Unit Single	1	3.44	48.80	9.50	4.70	2,178.92
Net single without Packaging	1	2.78	47.50	8.50	4.00	0.00

**More images:**



**Safety notes**

- The UPS system must be absolutely dry before it is installed. Please allow the UPS system to acclimatize for at least two hours to adapt to the environment.
- Protect the UPS system from water or moisture.
- Avoid direct sunlight or installation near heat sources.
- Do not block any ventilation openings in the housing.
- Do not connect any devices or appliances that would overload the system.
- Lay cables so that nobody can step on them or trip over them.
- Do not connect any household appliances to the output sockets of the UPS system.
- Only connect the UPS system to an earthed and easily accessible socket.
- Only use VDE-tested, CE-marked mains connection cables at the input and outputs.
- Never disconnect the mains connection cable during operation as this would cancel the protective earthing of the UPS system and all connected loads.
- The UPS system has its own internal power source. The output sockets or output terminals of the UPS system can be energized even if the UPS system is not connected to the building cabling.
- To switch off the UPS system completely, first press the OFF/Enter button to disconnect the mains.
- Caution - Risk of electric shock. Even after disconnecting the device from the mains, the components inside the UPS system are still connected to the battery. There is a risk of electric shock.
- Only persons who are sufficiently familiar with batteries and the necessary safety precautions may replace batteries and monitor operation.
- Caution - Risk of electric shock. The battery circuit is not isolated from the input voltage. Dangerous voltages can occur between the battery terminals and the ground. Ensure that no voltage is present before touching!
- When replacing the batteries, install the same number and type of batteries.
- Do not open or destroy batteries. Leaking electrolyte can injure the skin and eyes and may be toxic.
- The appliance may only be opened and repaired by a trained specialist.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
 Auf dem Schüffel 3  
 Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)