

DIGITUS Gigabit Media Converter, RJ45 / SC

DN-82120-1
EAN 4016032293125



Gigabit Ethernet Media Converter, Multimode SC connector, 850nm, up to 0.5km

The media converters from DIGITUS® are the ideal solution for the migration of copper and fiber network signals. From now on, you are able to access the fiber technology and transfer network signals over several kilometers without renewing your whole network infrastructure. The huge variety of products fulfil your individual needs. The intuitive operation guarantees a quick and easy installation. Years of experience and a wide range of products lets DIGITUS® become a reliable partner for your network.

The perfect converter solution for various fiber media

- Transforms wire based network media to fiber optic
- High quality and excellent reliability
- 10/100/1000Base-TX to 1000Base-SX
- Connectors: 1x RJ45, 1x SC duplex
- Distance up to 0.5km
- Wavelength: 850nm
- Multimode dual fiber
- Automatic cable detection - auto MDI / MDI-X function
- Auto-negotiation of full- and half-duplex
- Diagnostic and monitoring LEDs for the status of power, link and act of the ports
- Suitable for 50/125µm and 62.5/125µm Fiber Cables

- Transmission Power: Minimum -17 dBm, Maximum -12 dBm
- Sensitivity Receiving Power: Minimum -20 dBm
- Supported Standards: IEEE 802.3 Ethernet, IEEE 802.3u Fast Ethernet, IEEE 802.3z Gigabit Ethernet
- 2MB Data Buffer
- Operating Temperature: 0 to 60°C
- Dimensions (L x W x H): 95mm x 70mm x 26mm
- Weight: 200g
- Standalone Converter with external power supply
- Input Supply Voltage: 5V DC

Attributes

- Connector 1: RJ45
- Connector 2: SC
- Mode: Multimode
- Distance (km): 0.5
- Industrial usage: no
- Broadcasting Mode: Unidirectional
- PoE injector: no
- Ethernet speed: Gigabit

Package contents

- Media Converter
- Quick installation guide
- Power adapter

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	20	9.00	30.00	27.00	55.00	44.55
Packaging Unit Inside	1	0.45	6.00	21.60	16.10	2,086.56
Packaging Unit Single	1	0.45	6.00	21.60	16.10	2,086.56
Net single without Packaging	0	0.18	12.00	7.00	2.60	218.40

The images show the PWR 1000M Media Converter from multiple angles. The front view shows the TX (Transmit) and RX (Receive) ports, the Link/Act, FP (Fault Protection), and TP (Temperature Protection) LEDs, and the UTP (Unshielded Twisted Pair) port. The top view shows the DC 5V power input and the ON/LED indicator. The rear view shows the TX, RX, and UTP ports. The specification table provides detailed information about the device's features and performance.

Model Name	Port Type	Speed	Protocol	Media	Max. Power	Max. Temp.	Max. Humidity	Max. Altitude
PWR-1000M-1	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-2	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-3	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-4	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-5	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-6	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-7	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-8	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-9	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-10	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-11	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-12	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-13	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-14	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-15	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-16	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-17	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-18	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-19	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-20	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-21	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-22	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-23	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-24	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-25	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-26	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-27	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-28	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-1000M-29	10/100/1000	10/100/1000	10/100/1000	10/100/1000	2.0W	50°C	95%	1000m
PWR-10								

- Avoid direct contact with light sources: Fiber optic cables, especially those with active light sources such as lasers (e.g. in optical communication systems), can emit dangerous radiation that can damage
- eyes. Take care never to look directly into the light of an optical fiber, even if the light source is invisible to the naked eye.
- When working with fiber optic cables, especially during tests or when working with lasers, protective goggles should always be worn to protect against harmful radiation.
- When plugging and unplugging the cable, only grasp the plug and do not pull directly on the cable.
- Do not kink or crush: Fiber optic cables are sensitive to mechanical stress.
- To protect cables from physical damage, they should be laid in special ducts or with protective materials
- Keep cable connectors clean: Fiber optic cables are sensitive to dust and dirt. Even small particles on the connectors can severely impair the signal quality.
- Cables should not be used in environments with extremely high or very low temperatures. Observe the product information on the maximum operating temperature of the cable
- Check cables regularly for visible damage such as cracks, kinks or signs of wear. Defective cables should be replaced immediately.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com