

# DIGITUS Charging station with 6 charging spots, 58W

DA-10083  
EAN 4016032482697



## USB Charging station with 6 Port With PD 3.0 and Qi Wireless Charging Pad

The USB Charging Station from DIGITUS® enables charging of up to 5 devices via cable and 1 device via Qi wireless charging. While the devices are charging, the charging station automatically detects the fastest charging rate for the connected devices to ensure optimal charging. 5 short cables are included with the charging station: 1x USB-A to USB-C, 1x USB C to USB-C, 2x USB-A to iPhone (Lightning), 1x USB-A to Micro USB. The top side is made of silicone, which prevents the devices from slipping or falling off. The top side can be removed easily and conveniently washed if it gets dirty.

### Simultaneous charging of up to 6 devices in compact desktop organizer

- Input voltage: 100-240 V
- Power output: 1x USB-C: 5V/3A, 9V/2A, 12V/1.5A
- Power output: 1x USB A: 5V/2.4A
- Power output: 2x USB A: 5V/3.0A (1+2)
- Power output: 3x USB A: 1x 5 V/2.4A, 1x 5 V 3A (1+2 / 3+4)

- Power output: 4x USB A: 2x 5 V/3A (1+2 / 3+4)
- Wireless port power output: 5W / 7.5W / 10W
- Excess current protection / short circuit protection
- Housing: Fire-resistant material
- Dimensions: L 225 x W 125 x H 74 mm
- Color: white / gray
- Weight: 544 g

### Attributes

- Style: Charger/Power supply

### Package contents

- 1x Charging station
- 2 Connection cables USB A to Apple Lightning
- 1 Connection cables USB A to USB-C
- 1 Connection cable USB-C to USB-C
- 1 Connection cable USB-A to Micro USB
- Connection cable with CEE-7/16 Euro plug (Type C)
- QIG (Quick Installation Guide)

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	10	9.04	44.00	49.50	19.40	42,253.20
Packaging Unit Inside	1	0.90	8.50	24.00	17.00	3,468.00
Packaging Unit Single	1	0.90	8.50	24.00	17.00	3,468.00
Net single without Packaging	1	0.67	7.40	22.50	12.50	0.00

**More images:**



**Safety notes**

- Use charging adapters or power supply units in accordance with the instructions in the operating instructions to ensure optimum performance.
- Connect the charging adapter to an easily accessible socket in the voltage range between 100-240 V AC.
- Disconnect the charging adapter from the socket after use.
- Do not use the charging adapter with electronic devices that are outside the specifications of the charging adapter.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)