DIGITUS® Network cabinet Unique series - 800x1000 mm (WxD)

DN-19 26U-8/10-B-1

EAN 4016032370789



26U network rack, Unique 1342x800x1000 mm, color black (RAL 9005)

[illegible] DIGITUS [illegible] Unique [illegible] 1000 [illegible] (RAL 7035) [illegible] (RAL 9005); [illegible]

[illegible] DIGITUS® Unique [illegible]

- [illegible] IP20
- [illegible] 4 [illegible]
- [illegible] ([illegible])
- [illegible] – 120°
- [illegible]
- [illegible]
- [illegible]
- [illegible] 4 [illegible]
- [illegible] 483 [illegible] (19“) [illegible]
- [illegible] 483 [illegible] (19“) [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]
- [illegible]

Attributes

- Cabinet type: Network cabinet
- Color: black, RAL 9005
- Depth: 1000 mm
- Front door: Glass door, single opening
- Load capacity: 1200 kg
- Rear door: Steel door and cable entry, double opening
- Side panels: Both sides
- Units: 26
- Width: 800 mm
- IP protection class: IP20
- Mounted: yes

Package contents

- Earthing cable set
- Installation set (screws, cage nuts, washers)
- 2 x key
- 4 x leveling foot, M10

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	1	89.00	105.00	85.00	139.20	1,242,360.00
Packaging Unit Inside	1	89.00	105.00	85.00	139.20	1,242,360.00
Packaging Unit Single	1	89.00	105.00	85.00	139.20	1,242,360.00
Net single without Packaging	1	0.00	100.00	80.00	134.20	0.00

Safety notes

- Ensure adequate ventilation to prevent the installed devices from overheating.
- Network cabinets should not be overfilled and the ventilation openings must not be blocked.

- Cables should be neatly routed and organized in cable ducts or trays.
- Use surge protection devices to protect sensitive devices from power surges or lightning strikes.
- Avoid moisture or wetness while observing the respective IP protection class.
- Ensure that the cabinet and the devices used are properly earthed.
- In regions with frequent thunderstorm activity, professional lightning protection should be integrated into the power supply.
- To avoid uneven loading, always mount the heaviest units at the bottom of the cabinet.
- Disconnect the installed devices from the power supply during maintenance or installation work.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
https://www.assmann.com
info@assmann.com