

DIGITUS 4-х портовый настольный коммутатор 10/100/1000 Мбит/с PoE Gigabit + 1x Uplink

DN-95330

EAN 4016032390275



Gigabit Ethernet PoE Switch 4-port PoE + 1-port uplink, 62W PoE budget

5-ти портовый настольный коммутатор DIGITUS Gigabit с четырьмя портами питания через сеть Ethernet, а также с одним дополнительным портом Uplink обеспечит значительное увеличение мощности и повышение эффективности Вашей сети. Поддержка стандарта PoE позволяет использовать один кабель (сетевой кабель) как для электропитания, так и для передачи данных. Позволяет значительно упростить подключение таких устройств, как например, точки доступа, сетевые камеры или IP-телефоны, а также значительно сокращает требуемый расход кабеля. Кроме этого позволяет также расширить сеть там, где отсутствует электропроводка или розетки. Коммутатор не нуждается в настройках и, таким образом, гарантирует быструю установку в сети без дополнительных трудностей. Бесшумная конструкция дополнительно обеспечивает бесшумную работу, что позволяет устройству стать идеальным решением для офисов и залов для проведения переговоров.

Сетевой коммутатор со встроенной передачей питания по кабелю Ethernet (PoE) для оптимального, экономичного и быстрого соединения в малые и средние сети

- 4-х портовый настольный коммутатор 10/100/1000 Мбит/с PoE Gigabit + 1x Uplink
- Стандарты Ethernet IEEE802.3/802.3u/802.3x/IEEE802.3 af/at
- Функция передачи питания по кабелю Ethernet (PoE) позволяет использовать для питания и передачи данных всего один кабель
- Общая мощность PoE: 62 ватт (порт 1-4)
- Поддержка стандарта PoE: Порт 1-4 (802.af, 15,4 Вт) или для двух портов (802.3.at, 30 Вт)
- Максимальная выходная мощность: 65 Вт

- Не требует конфигурации
- Светодиодные индикаторы состояния на каждом порте
- Контактный вывод PoE: V+ (RJ45 контактный вывод 1, 2) V- (RJ45 контактный вывод 3, 6)
- Защита от превышения напряжения и короткого замыкания
- Объединительная панель: 10 Гбит/с
- Таблица адресов MAC: 2 K
- Потребляемая мощность: не более 3 Вт.
- Размеры (Д x Ш x В): 140 мм x 95 мм x 39 мм
- Вес: 300g
- Цвет: черный

Attributes

- Number of ports: 4
- PoE Power budget: 62 W
- PoE standard: IEEE802.3at (PoE+)
- Ethernet speed: Gigabit
- Industrial usage: no
- Installation type: Desktop
- Managed: no
- Number of ports (Uplink): 1
- Outdoorsuitable: no
- PoE (Power over Ethernet): yes
- Protection against vanadism: no
- Uplink port connection: RJ45
- VLAN: no

Package contents

- 5-портовый коммутатор Gigabit PoE
- Блок питания
- Силовой кабель
- Руководство по эксплуатации

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	16	13.60	30.00	40.00	32.00	38,400.00
Packaging Unit Inside	1	0.85	14.00	19.50	7.00	1,911.00
Packaging Unit Single	1	0.85	14.00	19.50	7.00	1,911.00
Net single without Packaging	1	0.30	8.50	13.00	3.00	0.00

More images:



Safety notes

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and send it to an authorized service centre for repair
 - The mains cable, power supply unit or plug for the power supply is damaged or worn;
 - Liquid has penetrated the appliance;
 - The device has been exposed to rain or water;
 - The device has been dropped or the housing has been damaged;
 - The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com