

# DIGITUS Injetor Industrial Gigabit PoE+ 802.3 af/at

**DN-651112**  
**EAN 4016032445845**



## Industrial Gigabit PoE+ Injector 802.3at 60W power output, DIN rail and wall mount design,

Com o auxílio do injetor PoE Digitus reduz os seus custos em cabos na instalação de dispositivos compatíveis com PoE, como, por exemplo, câmeras de rede IP. A alimentação dos dados, bem como de energia para os seus dispositivos realiza-se apenas através de um cabo Ethernet. Assim, a colocação de um cabo de energia separado torna-se desnecessária e, deste modo, poderá ampliar a sua rede onde não existem tomadas ou condutas de eletricidade. O injetor é totalmente compatível com a norma IEEE802.3at Ultra PoE e fornece uma potência de saída de 60 Watt.

### Saída de potência elevada com 60 Watt

- Em conformidade com a norma 802.3af/at PoE
- Voltagem de tensão de saída de 45-56, 60 Watt
- Entrada LAN RJ45
- Saída LAN (RJ45), fonte de alimentação através de pino: 4/5(+), 7/8(-) e 3/6(+), 1/2(-)
- Ligação de cabo: 10/100/1000 Mbps
- A saída dispõe de uma limitação de corrente, um dispositivo de proteção contra curto-circuito, bem como de uma deteção de equipamento final e classificação automáticas
- Consumo de energia: Máx. 3W

- Temperatura de funcionamento: -40°C - 75°C
- Consumo em funcionamento em vazio inferior a 0.3W
- Caixa metálica compacta, robusta
- Excelente proteção contra curto-circuitos
- Proteção contra relâmpagos e sobretensão
- Calha DIN (calha de sustentação) e possibilidade de montagem na parede

### Attributes

- PoE Power budget: 60 W
- PoE standard: IEEE802.3at (PoE+)
- Ethernet speed: Gigabit
- Power output: Depending on power supply
- Industrial usage: yes
- Installation type: DIN rail
- Managed: no
- Outdoorsuitable: no
- PoE (Power over Ethernet): yes
- Protection against vanadlism: no
- VLAN: no

### Package contents

- Injetor Industrial Gigabit PoE+ 802.3 af/at
- Peso: 20 g

### Logistics

|                              | Number<br>(pcs) | Weight<br>(kg) | Depth<br>(cm) | Width<br>(cm) | Height<br>(cm) | cm <sup>3</sup> |
|------------------------------|-----------------|----------------|---------------|---------------|----------------|-----------------|
| Packaging Unit Carton        | 36              | 14.76          | 39.00         | 35.00         | 33.00          | 45,045.00       |
| Packaging Unit Inside        | 1               | 0.41           | 16.50         | 12.50         | 5.00           | 1,031.25        |
| Packaging Unit Single        | 1               | 0.41           | 16.50         | 12.50         | 5.00           | 1,031.25        |
| Net single without Packaging | 1               | 0.30           | 10.30         | 7.70          | 3.20           | 0.00            |

**More images:****Safety notes**

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and return it to an authorized service centre for repair
  - The mains cable, power supply unit or plug for the power supply is damaged or worn;
  - Liquid has penetrated the appliance;
  - The device has been exposed to rain or water;
  - The device has been dropped or the housing has been damaged;
  - The function of the device has obviously changed;
  - The appliance cannot be operated as described in the operating instructions.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
info@assmann.com