

# DIGITUS® Aluminum Outlet Strip, 6 safety outlets with circuit breaker

DN-95417

EAN 4016032456636



## 1U Aluminum PDU, rackmountable, 6x safety outlet 16A, 4000W, 250VAC 50/60Hz, 1x circuit breaker

Order and flexibility in the server rack with the DIGITUS® professional socket strips. Plug your devices centrally into the 45° arranged shockproof sockets. Therefore, blocked or obscured adjacent sockets are a thing of the past. The socket strips are perfectly suited for 482.6 mm (19") server racks and network cabinets and offer sophisticated features. With the supplied mounting brackets, the socket strip fits easily into the 482.6 mm (19") grid of your network cabinet and looks neatly arranged. Designed for horizontal mounting, with vertical mounting being possible as well. In addition, the mounting bracket can be fixed on the socket strip in 8 different positions, 45° and 90° in 4 directions. The supply lines to the socket strip are protected by the integrated circuit breaker, which prevents overloading of the feed cabling.

**Safety, order and flexibility in the server rack - the DIGITUS® 482.6 mm (19") socket strips.**

- Barva: stříbrný/černý

### Attributes

- Additional Features: Circuit breaker
- Current: 16 A
- Input Plug: CEE7/7
- Installation: Desktop, Rack OU, Rack 1U
- Outlets: CEE 7/3
- Phase: 1ph
- Power: 3,6 kVA
- Volts: 230 V
- Inch form factor (IEC 60297): 482.6 mm (19")

### Package contents

- QIG (průvodce rychlou instalací)

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm <sup>3</sup>
Packaging Unit Carton	10	8.00	48.00	37.00	32.00	56,832.00
Packaging Unit Inside	1	0.80	12.00	65.00	5.80	4,524.00
Packaging Unit Single	1	0.80	78.00	12.00	8.50	7,956.00
Net single without Packaging	1	0.62	4.40	48.20	4.40	0.00

**More images:**



**Safety notes**

- This product is not intended for unsupervised use by children or persons under their care!
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Multiple sockets are not designed for permanent use with heavy loads!
- Multiple sockets must not be cascaded (avoid stringing together several multiple sockets).
- The maximum connected load must not be exceeded.
- Defective multiple sockets must be taken out of service immediately and disposed of in an environmentally friendly manner.
- In the event of a fault, take the product out of operation and contact a qualified electrician.
- Do not open the product.
- Disconnect the product from the power supply before cleaning. Do not use any aggressive or abrasive cleaning agents for cleaning.
- The ingress of liquids can lead to a short circuit.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
 Auf dem Schüffel 3  
 Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)