

DIGITUS Socket strip with aluminum profile and surge protection, integrated line filter, 6 safety sockets, 2 m cable safety plug

DN-95432

EAN 4016032483588



1U Aluminum PDU, rackmountable, 6 x Safety outlet 16A, 230VAC, 50/60Hz, Überspannungsschutz, Netzfilter

The DIGITUS® socket strips are the perfect solution for your network or server cabinet. With regard to current distribution, the PDU fulfills the requirements of many applications in IT, network technology, laboratories and also home use. The socket strip can be compactly mounted in the cabinet in the 19" area of 1U. An integrated line filter and surge protection protect the connected consumers against disruptions from the grid. It is possible, depending on the type of cabinet, to mount the power strip with the taps facing right or left.

Safe and professional current supply in the 19" network / server cabinet range

- Integrated line filter
- Integrated surge protection: Nominal
- discharge current (In) - 10 kA
- Socket rotation: 35°
- Housing: Aluminum
- Plastic components made of ABS UL-94V-0

- Input: Plug grounding contact CEE 7/7, 230 Vac / 16 A
- Output: Device socket 6 x grounding contact DIN 49440, max. 16 A per output
- Cable: H05VV-F 3G 1.5 mm², length: 2 m
- Dimensions: 482.6 (19") x 45 (1U) x 45 mm (HxWxD)

Attributes

- Additional Features: Overvoltage protection, Line filter
- Current: 16 A
- Input Plug: CEE7/7
- Installation: Rack 1U
- Outlets: CEE 7/3
- Phase: 1ph
- Power: 3,6 kVA
- Volts: 230 V
- Inch form factor (IEC 60297): 482.6 mm (19")

Package contents

- Scope of delivery: 1 socket strip, 2 mounting brackets; 1 safety instructions

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	10	11.82	19.50	52.00	29.50	29,913.00
Packaging Unit Inside	1	1.18	5.80	9.70	51.00	2,869.26
Packaging Unit Single	1	1.18	9.70	51.00	5.80	2,869.26
Net single without Packaging	1	0.85	4.50	48.30	4.50	0.00

Safety notes

- This product is not intended for unsupervised use by children or persons under their care!
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Multiple sockets are not designed for permanent use with heavy loads!
- Multiple sockets must not be cascaded (avoid stringing together several multiple sockets).
- The maximum connected load must not be exceeded.
- Defective multiple sockets must be taken out of service immediately and disposed of in an environmentally friendly manner.
- In the event of a fault, take the product out of operation and contact a qualified electrician.
- Do not open the product.
- Disconnect the product from the power supply before cleaning. Do not use any aggressive or abrasive cleaning agents for cleaning.
- The ingress of liquids can lead to a short circuit.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH

Auf dem Schüffel 3

Lüdenscheid, Germany

<https://www.assmann.com>

info@assmann.com