

Digitus® Rasprskivač struje s aluminijским profilom i zaštitom od prenaponskih udara, integriranim filtrom mreže, 6-putnom sigurnosnom utičnicom, 2 m napojnim kabeom, sigurnosnim u

DN-95432

EAN 4016032483588



1U Aluminum PDU, rackmountable, 6 x Safety outlet 16A, 230VAC, 50/60Hz, Overvoltage protection

DIGITUS® produžni kabeli savršeno su rješenje za vaš mrežni ili serverski ormar. Što se tiče raspodjele napajanja, PDU ispunjava zahtjeve mnogih primjena u IT-u, mrežnoj tehnologiji, laboratorijima pa čak i kod kuće. Rasprskivač se može montirati u 19-inčnom prostoru ormara u prostorno štedljivoj 1U konfiguraciji. Integrirani filter mrežne napetosti i zaštita od prenaponskih udara štite priključene uređaje od smetnji na mreži. Ovisno o vrsti ormara, rasprskivač se može montirati s utičnicama okrenutima udesno ili ulijevo.

Sigurno i profesionalno napajanje u području 19" mrežnih/server kabineta

- Integrirani mrežni filter
- Integrirana zaštita od prenapona: nominalna
- Iscjedna struja (In) – 10 kA
- Rotacija izlazaka: 45°
- Materijal: aluminij
- Plastične komponente izrađene od ABS-a UL-94V-0

- Uvod: sigurnosni utikač CEE 7/7, 230 V AC / 16 A
- Izlaz: Utičnice za uređaje 6 x uzemljenih utičnica DIN 49440, max. 16 A po izlazu
- Napojni kabel: H05VV-F 3G 1,5 mm², duljina: 2 m
- Dimenzije: 482,6 (19") x 45 (1U) x 45 mm (VxŠxD)

Attributes

- Dodatne mogućnosti: Zaštita od prenapona, Linijski filter
- El. snaga: 3,6 kVA
- Faze: 1 fazni
- Izlazni priključci: CEE 7/3
- Struja: 16 A
- Ugrađivanje: Stalak 1U
- Ulazni utikač: CEE7/7
- Volti: 230 V
- Inčni faktor oblika (IEC 60297): 482,6 mm (19")

Package contents

- Opseg isporuke: 1 produžni kabel, 2 nosača za montažu; 1 upute o sigurnosti

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	10	11.82	19.50	52.00	29.50	29,913.00
Packaging Unit Inside	1	1.18	5.80	9.70	51.00	2,869.26
Packaging Unit Single	1	1.18	9.70	51.00	5.80	2,869.26
Net single without Packaging	1	0.85	4.50	48.30	4.50	0.00

More images:



Safety notes

- This product is not intended for unsupervised use by children or persons under their care!
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Multiple sockets are not designed for permanent use with heavy loads!
- Multiple sockets must not be cascaded (avoid stringing together several multiple sockets).
- The maximum connected load must not be exceeded.
- Defective multiple sockets must be taken out of service immediately and disposed of in an environmentally friendly manner.
- In the event of a fault, take the product out of operation and contact a qualified electrician.
- Do not open the product.
- Disconnect the product from the power supply before cleaning. Do not use any aggressive or abrasive cleaning agents for cleaning.
- The ingress of liquids can lead to a short circuit.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schöffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com