

# Digitus® Socket strip with aluminum profile with switch and overvoltage protection, 12-way socket outlet with earthing contact, 2 m supply cable with earthing contact plug

DN-95435

EAN 4016032483618



## 1U Aluminum PDU, rackmountable, 12 x Safety outlet 16A, 230VAC, 50/60Hz, overvoltage, Switch

The DIGITUS® power strips are the perfect solution for your network or server cabinet. In terms of power distribution, the PDU meets the requirements of many applications in IT, network technology, laboratories and the home. The power strip can be mounted vertically in the cabinet. Overvoltage protection protects consumers from overvoltage. Depending on the type of cabinet, it is possible to mount the socket strip with the taps pointing to the right or left.

### Secure and professional power supply in the network / server rack area

- Vertical installation
- Illuminated switch - to prevent accidental
- Overvoltage protection module against overvoltage
- Overvoltage protection : Nominal discharge current (In) - 5 kA
- Rotation of the cans: 45°
- Housing: Aluminum
- Plastic components made of ABS UL-94V-0

- Input: earthing contact plug CEE 7/7, 230 Vac / 16 A
- Output: appliance sockets 12 x socket outlet with earthing contact DIN 49440, max. 16 A per output
- Supply cable: H05VV-F 3G 1.5 mm<sup>2</sup>, length: 2 m
- Dimensions: 762 x 45 x 45 mm (HxWxD)





### Attributes

- Additional Features: Power switch, Overvoltage protection
- Current: 16 A
- Input Plug: CEE7/7
- Installation: Rack OU
- Outlets: CEE 7/3
- Phase: 1ph
- Power: 3,6 kVA
- Volts: 230 V

### Package contents

- Scope of delivery: 1 socket strip, 2 mounting brackets; 1 safety instructions

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm <sup>3</sup>
<b>Packaging Unit Carton</b>	10	4.86	26.50	91.00	31.50	75,962.20
<b>Packaging Unit Inside</b>	1	0.49	0.00	0.00	0.00	0.00
<b>Packaging Unit Single</b>	1	0.49	12.00	90.00	5.80	6,264.00
<b>Net single without Packaging</b>	1	1.20	4.50	76.20	4.50	0.00

**More images:****Safety notes**

- This product is not intended for unsupervised use by children or persons under their care!
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Multiple sockets are not designed for permanent use with heavy loads!
- Multiple sockets must not be cascaded (avoid stringing together several multiple sockets).
- The maximum connected load must not be exceeded.
- Defective multiple sockets must be taken out of service immediately and disposed of in an environmentally friendly manner.
- In the event of a fault, take the product out of operation and contact a qualified electrician.
- Do not open the product.
- Disconnect the product from the power supply before cleaning. Do not use any aggressive or abrasive cleaning agents for cleaning.
- The ingress of liquids can lead to a short circuit.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)