

Digitus® Rasprskivač struje s aluminijским profilom i zaštitom od prenapona, integrirani filter mreže, 9-putna sigurnosna utičnica, 2 m napojni kabel, sigurnosni utikač

DN-95438

EAN 4016032501657



Aluminium PDU, Rackmountable, frequency filter, 2m 16A, 3600W, 230VAC 50/60Hz, 9x safety outlet

DIGITUS® produžni kabeli savršeno su rješenje za vaš mrežni ili serverski ormar. Što se tiče raspodjele električne energije, PDU zadovoljava zahtjeve mnogih primjena u IT-u, mrežnoj tehnologiji, laboratorijima pa čak i kod kuće. Rasprskivač se može montirati okomito u ormaru. Integrirani filter mrežne napetosti i zaštita od prenapona štite priključene uređaje od smetnji u napajanju. Ovisno o vrsti ormara, rasprskivač se može montirati s utičnicama okrenutima udesno ili ulijevo.

Sigurno i profesionalno napajanje u prostoru mrežnog/poslužiteljskog ormara

- Integrirani mrežni filter
- Integrirana zaštita od prenapona: nominalna ispusna struja (In) - 10 kA
- Postavljanje vertikalne police
- Rotacija limenki: 45°
- Materijal: aluminij
- Plastične komponente izrađene od ABS-a UL-94V-0

- Uvod: sigurnosni utikač CEE 7/7, 230 V AC / 16 A
- Izlaz: Utičnice za uređaje 9 x uzemljenih utičnica DIN 49440, max. 16 A po izlazu
- Napojni kabel: H05VV-F 3G 1,5 mm², duljina: 2 m
- Dimenzije: 620 x 45 x 45 mm (VxŠxD)

Attributes

- Dodatne mogućnosti: Linijski filter
- Izlazni priključci: CEE 7/3
- Mjerenje: Mjerenje izlaza
- Struja: 16 A
- Ugrađivanje: Stalak 1U
- Ulazni utikač: CEE7/7
- Volti: 230 V
- Inčni faktor oblika (IEC 60297): 482,6 mm (19")

Package contents

- Opseg isporuke: 1 produžni kabel, 2 nosača za montažu; 1 upute o sigurnosti

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	10	12.15	26.50	76.50	31.00	62,844.80
Packaging Unit Inside	1	1.22	5.80	12.00	75.00	5,220.00
Packaging Unit Single	1	1.22	5.80	12.00	75.00	5,220.00
Net single without Packaging	1	0.90	4.50	4.50	62.00	0.00

More images:



Safety notes

- This product is not intended for unsupervised use by children or persons under their care!
- Prevent higher humidity or temperatures than those specified in the data sheet – Avoid moisture, dust or vapors, solvents, flammable gases.
- Multiple sockets are not designed for permanent use with heavy loads!
- Multiple sockets must not be cascaded (avoid stringing together several multiple sockets).
- The maximum connected load must not be exceeded.
- Defective multiple sockets must be taken out of service immediately and disposed of in an environmentally friendly manner.
- In the event of a fault, take the product out of operation and contact a qualified electrician.
- Do not open the product.
- Disconnect the product from the power supply before cleaning. Do not use any aggressive or abrasive cleaning agents for cleaning.
- The ingress of liquids can lead to a short circuit.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schöffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com