

# DIGITUS® KVM switch, 2-port, triple display, 4K, DisplayPort

DS-12864

EAN 4016032510215



## KVM-Switch, 2-Port, Triple Display 4K, Displayport Output

With the DIGITUS 2-port KVM switch for triple displays, you have the option of operating two 4K-capable PCs via a single USB keyboard and mouse combination. You can conveniently switch between the two PCs at the touch of a button or hotkey and save yourself the hassle of having to reconnect all the cables. Output to up to three monitors is via the three native DisplayPort outputs on the rear - ideal for professional workstations and CAD environments with a DisplayPort infrastructure. Audio signals from the microphone and speakers are also switched. There are also two USB 3.0 ports on the front, which can be used for additional peripheral devices such as USB sticks or printers on both PCs. The connected peripheral devices are each assigned to the active PC. Status LEDs on the front of the switch indicate the current configuration at all times.

**Operate two 4K-capable PCs via a single USB keyboard and mouse combination and conveniently switch between the two PCs at the touch of a button or hotkey.**

- Inputs:
- 2× HDMI Type-A female (black)
- 4× DisplayPort Type-A female (black)
- 2× USB Type-B female (keyboard/mouse, per PC)

- 2× mini jack 3.5 mm black (audio + MIC, per PC)
- Outputs:
- 3× DisplayPort Type-A female (black)
- 1× USB Type-A female (keyboard)
- 1× USB Type-A female (mouse)
- 1× mini-jack 3.5 mm green (loudspeaker)
- 1× mini-jack 3.5 mm pink (microphone)
- Front connections: 2× USB 3.0 Type-A blue female
- Max. Resolution: 4K@60Hz (3840×2160)
- Switching: Front button (2×) / Hotkey (4 modes)
- Standard hotkey: [Ctrl]+[Ctrl] (can be switched to Scroll/Num/Caps)
- Front LEDs: 2× red (online), 2× green (active selected)
- Power supply: DC 5V/2A, socket 5.5×2.1 mm (external)
- Housing: Aluminum alloy
- Dimensions (W×D×H): 161 × 105 × 78 mm
- Weight: 1.74 kg

### Package contents

- KVM switch
- 6× KVM cable set (1.8 m)
- User manual

## Logistics

|                                 | Number<br>(pcs) | Weight<br>(kg) | Depth<br>(cm) | Width<br>(cm) | Height<br>(cm) | cm³       |
|---------------------------------|-----------------|----------------|---------------|---------------|----------------|-----------|
| Packaging Unit Carton           | 8               | 18.40          | 49.20         | 33.00         | 45.40          | 73,711.40 |
| Packaging Unit Inside           | 1               | 2.30           | 0.00          | 0.00          | 0.00           | 0.00      |
| Packaging Unit Single           | 1               | 2.30           | 16.00         | 22.00         | 24.00          | 8,448.00  |
| Net single without<br>Packaging | 1               | 0.64           | 7.80          | 10.50         | 16.10          | 0.00      |

## More images:



## Safety notes

- Overloading can lead to overheating and damage to the appliance or the connected peripherals.
- If necessary, use an external power supply to ensure stable performance.
- If devices such as external hard disks or printers that require a high power consumption are connected, the device should be used with an external power supply. Otherwise, the device could be overloaded or functional problems could occur.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

## EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schöffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)