

DIGITUS 2 Port-Gigabit-Ethernet-PoE-Switch, Industrie, unverwaltet, 1 SFP-Uplink

DN-652120

EAN 4016032482925



Industrial Media Converter 10/100/1000Base-TX (PoE) to 1000Base-FX

Industrial PoE Ethernet switch with 2-Port 10/100/1000Mbps RJ45(PoE) +1 Port 1000Mbps SFP, the Product meet CE, RoHS standards. DN-652120 switch has the operating temperature of -40 ~80, has the super firmness can adapt to all kinds of harsh environment, can also be conveniently placed in the compact space of the control box. The installation characteristics of the guide rail, wide temperature operation, IP40 protection class housing and LED indicator light make the DN-652120 a plug and play industrial grade device, providing a reliable and convenient solution for users to network their Ethernet devices.

Industrial PoE Ethernet switch with 2-Port 10/100/1000Mbps RJ45(PoE) +1 Port 1000Mbps SFP

- Ensure reliable data transmission
- Support full duplex or half duplex mode, with automatic negotiation capability
- Network port support automatic cross identification
- Internal storage and forwarding mechanism, support a variety of protocols
- In line with industrial operating standards, the average trouble-free work in more than 300,000 hours
- Working power supply: DC 48-57V to provide reverse protection
- Standard: IEEE802.310BASE-TIEEE802.3i 10Base-T;IEEE802.3u;100Base-TX/FX;IEEE802.3ab1000Base-T;IEEE802.3z1000Base-X;IEEE802.3x; IEEE802.3af, IEEE802.3at

- Work environment: -40~80 °C
- Storage: -40~80 °C
- Bandwidth: 14Gbps
- Packet Buffer Memory:1.2Mbit
- Packet Forwarding Rate:10.5Mpps
- MAC Address Table: 2K
- Power supply: input voltage: DC48-57V
- two-way power redundancy backup
- Support reverse connection protection
- IP40 aluminum housing
- DIN rail install
- Natural cooling, no fan
- Weight: 0.42Kgs
- Measurement: 118 x 92.4 x 40 mm
- Total PoE Power budget (W): 60W

Attributes

- Connector 1: RJ45
- Connector 2: SFP
- Connector: RJ45
- DDM Support: no
- Industrial usage: yes
- PoE injector: yes

Package contents

- industrial Switch 2xRJ45 1xSFP
- User Manual

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	24	10.08	0.00	0.00	0.00	0.00
Packaging Unit Inside	1	0.42	0.00	0.00	0.00	0.00
Packaging Unit Single	1	0.42	0.00	0.00	0.00	0.00
Net single without Packaging	0	0.00	0.00	0.00	0.00	384.00

More images:



Safety notes

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and send it to an authorized service centre for repair
 - The mains cable, power supply unit or plug for the power supply is damaged or worn;
 - Liquid has penetrated the appliance;
 - The device has been exposed to rain or water;
 - The device has been dropped or the housing has been damaged;
 - The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com