

DIGITUS USB 2.0 serial adapter

DA-70156
EAN 4016032271611



USB 2.0 to serial Converter, DSUB 9M incl. USB A Cable 80cm, FTDI chipset

The DIGITUS® USB2.0 serial adapter offers a practical solution for providing serial connectivity. A serial RS232 interface is no longer available on newer hardware. The DIGITUS® USB2.0 serial adapter enables data exchange between a USB2.0 port on the computer and peripheral devices with a serial interface (COM port, RS232), such as weather stations, sensors, machine controls, set-top boxes, games consoles, PDAs, scanners, modems, ISDN adapters and many other peripheral devices. The USB2.0 serial adapter is downwards compatible with USB1.1 and enables customizable baud rates between 75 bits and 128,000 bits per second. The individually configurable FTDI chipset ensures compatibility with all common operating systems and also supports power management and remote wake-up. Power is supplied via the USB port; a separate power supply unit is not required.

Provides a serial RS232 interface via USB2.0

- Provides a serial RS232 interface via USB 2.0

- Complies with the USB 2.0 standard
- Backwards compatibility with USB 1.1
- Customizable data transfer rates between 75 bits and 128,000 bits per second
- Supports remote wake-up and power management
- Chipset: FTDI / FT232RNL
- Individual configuration via the FTDI chipset
- 1× RS232 plug (Sub D 9-pin) / 1× USB A plug
- Interface: Full Duplex
- Gold-plated contacts
- Incl. USB extension cable, approx. 80 cm
- Supports Windows 11, 10, 8.1, 8, 7, Vista, XP, Mac OS X and Linux
- True 5V / 3.3V / 2.8V / 1.8V CMOS output and TTL input

Package contents

- USB - Serial Adapter
- USB extension cable
- Driver CD

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	150	13.00	50.40	21.30	47.00	0.00
Packaging Unit Inside	1	0.09	18.50	8.50	2.30	361,675.00
Packaging Unit Single	1	0.09	9.00	9.00	3.00	243.00
Net single without Packaging	0	22.00	7.40	1.80	1.50	19.98

More images:



Safety notes

- Overloading can lead to overheating and damage to the appliance or the connected peripherals.
- If necessary, use an external power supply to ensure stable performance.
- If devices such as external hard disks or printers that require a high power consumption are connected, the device should be used with an external power supply. Otherwise, the device could be overloaded or functional problems could occur.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com