

# DIGITUS® Wall Mounting Cabinets - Slim

DN-19 WM-V6U-SL  
EAN 4016032383260



**Wall mounting cabinet, slim 800x640x309 mm, 6U vertical, color grey (RAL 7035)**

The 483 mm (19") Wall Mounting Cabinet of the Sim Series allows a vertical mounting of 6U in depth. Especially space saving for networks, DVR, sound equipment, paging- and patching applications or other 483 mm (19") active components.

**Slim design with mounting profiles for vertical installations inside**

- 1.0 - 1.5 mm strong steel sheet
- 483 mm (19") mounting areas inside: 6U in depth
- Punched out cable entries with plastic cover on all sides (145x70 mm)
- Bottom is prepared for fan units
- Lockable front door with air ventilation slots
- Door stop is easy to change
- Packaging dimensions (HxWxD): 820x660x320 mm
- Max. equipment mounting height inside: 610 mm

**Attributes**

- Bočne ploče: Obje strane
- Boja: svijetlo siva, RAL 7035
- Dubina: 309 mm
- Jedinice: 6
- Kapacitet opterećenja: 100 kg
- Prednja vrata: Čelična vrata, zatvorena, jednostruko otvaranje
- Širina: 640 mm
- Vrsta ormara: Zidni ormarić, kućna automatika
- IP klasa zaštite: IP20
- Montirano: Da

**Package contents**

- Earthing wire set
- 2 x Keys

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	1	21.00	32.00	66.00	82.00	173.18
Packaging Unit Inside	1	21.00	32.00	66.00	82.00	173.18
Packaging Unit Single	1	21.00	32.00	66.00	82.00	173.18
Net single without Packaging	0	19.00	30.90	64.00	80.00	158.21

**More images:**



**Safety notes**

- Ensure adequate ventilation to prevent the installed devices from overheating.
- Network cabinets should not be overfilled and the ventilation openings must not be blocked.
- Cables should be laid neatly and organized in cable ducts or trays.
- Use surge protection devices to protect sensitive devices from power surges or lightning strikes.
- Avoid moisture or wetness while observing the respective IP protection class.
- Ensure that the cabinet and the devices used are properly earthed.
- In regions with frequent thunderstorm activity, professional lightning protection should be integrated into the power supply.
- To avoid uneven loading, always mount the heaviest units at the bottom of the cabinet.
- Disconnect the installed devices from the power supply during maintenance or installation work.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)