

# DIGITUS® 6-way office power strip with 3x USB ports

DA-70624

EAN 4016032487012



### 6-fach Office power strip 3x USB 2xUSB-A +1xUSB A, On/off switch, Alu-housing

Forget times when you had to look for your smartphone charger constantly. The office power strip from DIGITUS® even provides you with 3 USB ports where you can charge your smartphone and your tablet simultaneously, for example. Use all protective contact sockets without connection problems. Use all safety sockets without connecting problems because of the smart 45° degree layout. You can even use bigger and bulky right angle plugs without blocking or covering the other nearby safety sockets. Furthermore you have the opportunity to set up the socket strip variably and fix it on demand by the clamping assembly perfectly to your location. Once clamped, the bar can be rotated horizontally to ensure optimal flexibility. Protect yourself and your family from electric shocks with the integrated shutters and the resulting increased protection against accidental contact of the protective contact sockets. A big range of placing the socket strip is provided by its 1,5 m mains. The valuable aluminium housing and noble design completes this multi-function safety socket strip.

### 6-way power strip with three additional USB charging ports for mobile devices in a high-quality aluminum housing

- 6x protective contact sockets in a 45° arrangement, also suitable for bulky angle plugs

- 2x USB A ports (5V/3A, 9V/2A, 12V/1.5A, 18W max.) for charging mobile devices
- 1x USB-C port (5V/3A, 9V/2.2A, 12V/1.67A, 20W max.) for charging mobile devices
- 2x universal clamp mountings for different table thicknesses (20mm - 57mm)
- Illuminated safety switch for switching on and off
- Protection against accidental contact: Plastic covers close the contacts on the socket
- High-quality aluminium housing
- Mains cable with safety plug: 1.5 m
- Input voltage: 110 - 240 VAC
- Frequency: 50Hz
- Output power: 3680 W, 16 A max.
- Dimensions: L 44.0 x W 4.5 x H 7.0 cm
- Weight: 695 g
- Colour: silver/black

#### Attributes

- Style: Outlet strip

#### Package contents

- 6-way office power strip with 3x USB ports
- 2x clamp mountings
- User manual

### Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	20	15.50	38.00	45.00	50.00	85.50
Packaging Unit Inside	1	0.78	0.00	0.00	0.00	0.00
Packaging Unit Single	1	0.78	6.50	48.00	10.50	3.28
Net single without Packaging	0	0.73	6.00	43.50	6.50	1,696.50

**More images:**



**Safety notes**

- Only operate the device indoors. Avoid exposure to moisture, dust, sunlight or other sources of heat.
- The socket outlet is part of the building installation. The relevant national standards and directives must be observed during planning and installation.
- The appliance may only be operated on the 230V/50 Hz AC mains supply. Work on the 230V mains may only be carried out by a qualified electrician certified in your country.
- Observe the applicable accident prevention regulations during installation.
- To avoid electric shock to the appliance, please disconnect the mains voltage (e.g. switch off the circuit breaker).
- Failure to observe the installation instructions may result in fire or other hazards.
- Installation may only be carried out in commercially available flush-mounted boxes (appliance boxes) in accordance with DIN 49073-1, with a minimum depth of 40 mm.
- When connecting to the device terminals, observe the permissible cables and cable cross-sections.
- Mandatory information in accordance with the appliance safety standard
- Note!
- Installation only by persons with relevant electrical knowledge and experience!
- Improper installation puts your own life and the lives of the users of the electrical system at risk.
- You risk serious damage to property if the installation is not carried out correctly. You may be personally liable for personal injury and damage to property.
- Contact an electrician.
- Specialist knowledge required for installation:
- The following specialist knowledge in particular is required for installation:
- The application of the 5 safety rules 1. Disconnect 2. Secure against reconnection 3. Ensure there is no voltage 4. Earth and short-circuit 5. Cover or isolate neighboring live parts.
- Selection of suitable tools, measuring equipment and, if necessary, personal protective equipment.
- Selection of the electrical installation material to ensure the switch-off conditions.
- Check the electrical system after installation.
- Observing the IP protection classes
- Installation only with suitable electrical installation material
- Check and observe the respective specifications of the type of supply network (TN system, TT system or IT system) and the resulting connection conditions (zeroing, protective earthing, or any additional measures required, etc.).
- Maintenance and cleaning:
- The socket is maintenance-free.
- Leave repairs to a qualified electrician.
- Only clean the device with a soft, clean, dry and lint-free cloth.
- Do not use cleaning agents containing solvents. This can damage the plastic housing.

- Do not use wet cloths or sponges to clean the appliance.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)