

NVMe cloning station USB3.1 Gen2 Type-C NVMe M.2 SSD enclosure

DA-71545-1
EAN 4016032501381



Dual Bay Nvme SSD Docking Station 2 bay NVME duplicator M.2 SSD Docking Station

The DIGITUS® Dual NVMe Docking Station DA-71545-1 offers a powerful storage solution for IT professionals and enthusiasts. With space for two M.2 NVMe SSDs (up to 4 TB per slot), it enables high-speed data transfers and an integrated offline cloning function that allows easy duplication of data carriers at the touch of a button.

Manage M.2 NVMe and M.2 SATA SSDs via a USB-C™ connection

- Capacity: Maximum 4 TB per slot, total: Up to 8 TB storage space
- Supported SSD formats: M-Key & B+M-Key SSDs (NVMe), Sizes: 2242, 2260, 2280 & 22110
- Connections: □USB-C™ (data): USB 3.2 Gen2 □USB-C™ (power supply): 5 V / 3 A
- Maximum transmission speed: 10 Gbps

- Modes: Clone mode (offline cloning function without PC), dual mode (simultaneous use of both SSDs)
- Compatible devices: PCs, notebooks, NAS, smart TVs, routers, gaming consoles (with USB-C™ connection)
- Supported file systems: NTFS, FAT, FAT32
- Power supply: Input: 100 - 240 V AC / 50/60 Hz, 0.6 A (Euro plug type A CEE 7/16), output: 5 V / 3 A via USB-C™
- Supported operating systems: □Windows 11/10/8/8.1/7/XP □macOS 10.0 or higher □Linux
- Dimensions & weight: □Dimensions (W x D x H): 7.9 x 7.7 x 1.8 cm □Weight: 152 g

Package contents

- NVMe cloning station
- USB A to USB C connection cable
- USB C to USB C connection cable
- Power supply unit 5V, 3A, 15W

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	20	6.90	32.50	35.50	24.00	27,690.00
Packaging Unit Inside	1	0.35	0.00	0.00	0.00	0.00
Packaging Unit Single	1	0.35	10.60	15.00	7.00	1,113.00
Net single without Packaging	0	0.12	6.60	10.20	1.50	100.98

More images:





Safety notes

- Overloading can lead to overheating and damage to the appliance or the connected peripherals.
- If necessary, use an external power supply to ensure stable performance.
- If devices such as external hard disks or printers that require a high power consumption are connected, the device should be used with an external power supply. Otherwise, the device could be overloaded or functional problems could occur.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.