

# DIGITUS 16 port Gigabit Ethernet network switch, industrial, unmanaged, 2 SFP uplink

DN-651138

EAN 4016032486084



## Industrial 16+2 -Port Gigabit Ethernet Switch Unmanaged, 16 RJ45 Ports 10/100/1000 Mbps

DN-651138 is an industrial Gigabit Ethernet switch with 16 port 10/100/1000 Mbps RJ45 +2 port 1000 Mbps base-FX. The industrial switch has the operating temperature of -40° ~ 80°, has been manufactured ruggedly and can be used in all kinds of harsh environments. The switch can be easily installed on a free DIN rail. The wide temperature range, IP40-rated housing and LED indicator make the DN-651138 an industrial-grade plug-and-play device that provides users with a reliable and convenient solution for networking their Ethernet devices.

**The DN-651138 is a 16+2 port Gigabit Ethernet switch suitable for industrial applications (IP40) that offers interference-free data transfer performance in harsh industrial environments.**

- 16 ports 10/100/1000 Base-Tx RJ45 with auto-negotiation and Auto-MDI/ MDI-X function
- 2-port SFP uplink
- 12V to 52V DC, redundant power connection possible
- Operating temperature: - 40° to 80°
- IP40 aluminum housing
- Supports 6KV DC Ethernet ESD protection
- Supports 6KV DC EFT protection for the power line
- Vibration, shock and drop protection
- Easy installation on DIN rail
- Performance specification: Bandwidth: 52Gbps, Packet buffer memory: 4.1Mbit, Packet forwarding rate: 38.7Mpps, MAC address table: 8K
- Flow control: utilizes backpressure technology for half-duplex, utilizes "pause frame" technology in full-duplex mode
- Housing: aluminum housing with protection class IP40

- LED display: Power: Red, Ethernet: Yellow
- Power input: 48 to 57V DC, it is possible to install a redundant power supply
- Power consumption: < 10 watts
- Network protocols: IEEE802.3 10BASE-T; IEEE802.3i 10Base-T; IEEE802.3u;100Base-TX/FX; IEEE802.3ab 1000Base-T; IEEE802.3z 1000Base-X; IEEE802.3x
- " Industry standard: IEC 61000-4-4 (EFT), Level 3 IEC 61000-4-5 (Surge), Level 3 Shock: IEC 60068-2-27 Free fall: IEC 60068-2-32 Vibration: IEC 60068-2-6"
- Dimensions (W x D x H): 175.6 x 135 x 45.5 mm
- Weight: Product weight: 1.0KGS
- Working environment: Operating temperature: -40 to max 80°; Storage temperature: -40 to max 80°
- Relative humidity: 5% to max. 95% (no condensation)

### Attributes

- Number of ports: 16
- Ethernet speed: Gigabit
- Industrial usage: yes
- Managed: no
- Number of ports (Uplink): 2
- Outdoorsuitable: no
- PoE (Power over Ethernet): no
- Protection against vandalism: no
- Uplink port connection: SFP
- VLAN: no

### Package contents

- 16-port Ethernet switch
- Manual

| Logistics                    |              |             |            |            |             |           |
|------------------------------|--------------|-------------|------------|------------|-------------|-----------|
|                              | Number (pcs) | Weight (kg) | Depth (cm) | Width (cm) | Height (cm) | cm³       |
| Packaging Unit Carton        | 12           | 13.70       | 46.50      | 39.50      | 24.00       | 44,082.00 |
| Packaging Unit Inside        | 1            | 1.14        | 0.00       | 0.00       | 0.00        | 0.00      |
| Packaging Unit Single        | 1            | 1.14        | 7.25       | 18.60      | 20.80       | 2,804.88  |
| Net single without Packaging | 1            | 1.03        | 7.25       | 18.60      | 20.80       | 2,804.88  |

**Safety notes**

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and send it to an authorized service centre for repair
  - The mains cable, power supply unit or plug for the power supply is damaged or worn;
  - Liquid has penetrated the appliance;
  - The device has been exposed to rain or water;
  - The device has been dropped or the housing has been damaged;
  - The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schöffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)