

DIGITUS USB 3.0 to SATA III Adapter Cable

DA-70326
EAN 4016032308546



USB 3.0 to SATA3 Adapter Cable 1.2M including Power Supply

USB 3.0 to SATA3 Adapter Cable, 1.2M including Power Supply

Turns any SATA HDD/SSD into an ultra fast external USB 3.0 drive - Ideal for backup and service

- Capacity: up to 8 TB
- Supports 2,5/3,5 SATA HDD/SSD's
- Supports SATA 6.0 Gps/ 3.0 Gbps /1.5 Gbps speed negotiation
- Supports data transfer rate: Super-Speed(5 Gbps) / High-Speed(480 Mbps)/ Full-Speed(12 Mbps) / Low-Speed(1.5 Mbps)
- Compliant to USB 3.0 specification, downward compatible with USB 2.0 and USB 1.1

- USB mass storage class support
- Plug & play and hot-swappable
- Compliant to Serial ATA3
- High-Speed data transfer, low power consumption
- Incl. power supply, input: AC 100-240V, 50/60Hz, output: DC 12V2A
- 1.2M USB 3.0 to SATA III cable
- Supports Windows 10, 8, 7, Vista and XP

Package contents

- DIGITUS® USB 3.0 to SATA III adapter cable
- Powersupply

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm ³
Packaging Unit Carton	30	11.00	50.50	32.20	47.60	77,402.40
Packaging Unit Inside	1	0.37	23.50	15.00	6.00	2,115.00
Packaging Unit Single	1	0.37	23.50	15.00	6.00	2,115.00
Net single without Packaging	1	0.08	14.50	3.50	1.80	0.00

More images:



Safety notes

- Overloading can lead to overheating and damage to the appliance or the connected peripherals.

- If necessary, use an external power supply to ensure stable performance.
- If devices such as external hard disks or printers that require a high power consumption are connected, the device should be used with an external power supply. Otherwise, the device could be overloaded or functional problems could occur.
- Do not expose the device to rain, moisture, vapors or liquids.
- Do not insert any objects into the device.
- Do not attempt to repair the unit or open the housing without authorization. You risk an electric shock!
- Ensure adequate ventilation to prevent damage due to overheating.
- Dust, moisture, vapors and strong cleaning agents or solvents can cause damage to the device.
- Disconnect the appliance from the power supply and the connected devices before cleaning.
- Clean the device with a dust-free cloth.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com