

# DIGITUS Interruptor Gigabit PoE L2 gerido de 8 portas + 2 SFP

DN-95344

EAN 4016032455103



## L2 managed Gigabit Ethernet PoE Switch 8-port PoE + 2-port SFP, 86W PoE budget

O interruptor Gigabit PoE L2 gerido DIGITUS® com 8 portas PoE+ e 2 portas SFP Gigabit é ideal para utilizar com diferentes topologias de rede como, por exemplo, em PME. As inúmeras opções de configuração L2 podem aumentar o desempenho e a eficiência da sua rede. O interruptor proporciona a possibilidade de segmentar a rede via VLAN e a funcionalidade QoS garante uma troca de dados sem problemas em aplicações urgentes. Através do Protocolo Spanning Tree ou do Port Trunk, a segurança contra falhas pode ser criada ao estabelecer ligação com outros interruptores. A gestão dos interruptores pode ser realizada através da interface Web, SNMP, SSH ou Telnet.

### Funções de Alimentação via Ethernet (PoE) e gestão de rede integrada para ambientes de rede de pequena e média dimensão

- 8 portas 10/100/1000Base-T com suporte PoE
- Uplink SFP Gigabit de 2 Portas
- Saída de corrente PoE 44 ~ 57 V de corrente contínua, no máx. 30 W por porta
- Modo de alimentação de corrente PoE- A, PIN 1/2(+), 3/6(-)
- Configurações VLAN com base na porta / com base em etiqueta / com base em MAC / com base no IP / comando de voz VLAN / mapeamento VLAN / VLAN dupla
- Configurações Trunk, compatibilidade com Rapid Spanning Tree (IEEE802.1d STP, IEEE802.1w RSTP, IEEE802.1s MSTP)
- Suporte QoS
- Filtragem de endereços MAC, filtragem TCP/UDP
- Autenticação Tacacs+ e raio
- Fornece não bloqueamento, avanço de início de fila

- Suporta tomada de pressão e controlo de largura de banda em cada porta
- Tecnologia Store-and-Forward para uma transferência de dados ótima
- Velocidade automática e reconhecimento/ajustamento half/full duplex
- Função Auto-MDI-/MDI-X
- Backplane com 20 Gbps
- Suporta endereços MAC até 8K
- Potência de saída máxima 86 Watt

### Attributes

- Number of ports: 8
- PoE Power budget: 86 W
- PoE standard: IEEE802.3at (PoE+)
- Ethernet speed: Gigabit
- Industrial usage: no
- Installation type: Desktop, 19 inch
- Managed: yes
- Number of ports (Uplink): 2
- Outdoorsuitable: no
- PoE (Power over Ethernet): yes
- Protection against vandalism: no
- Uplink port connection: SFP
- VLAN: yes

### Package contents

- Interruptor Gigabit PoE L2 gerido de 8 portas
- Peso: 20 g
- Adaptador de corrente
- Acessórios de montagem

## Logistics

|                              | Number (pcs) | Weight (kg) | Depth (cm) | Width (cm) | Height (cm) | cm³       |
|------------------------------|--------------|-------------|------------|------------|-------------|-----------|
| Packaging Unit Carton        | 10           | 16.01       | 34.00      | 28.00      | 48.00       | 45,696.00 |
| Packaging Unit Inside        | 1            | 1.60        | 10.00      | 16.50      | 27.50       | 4,537.50  |
| Packaging Unit Single        | 1            | 1.60        | 3.90       | 11.50      | 25.00       | 1,121.25  |
| Net single without Packaging | 1            | 0.67        | 3.90       | 11.50      | 25.00       | 0.00      |

# More images:



## Safety notes

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.
- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and send it to an authorized service centre for repair
- The mains cable, power supply unit or plug for the power supply is damaged or worn;

- Liquid has penetrated the appliance;
- The device has been exposed to rain or water;
- The device has been dropped or the housing has been damaged;
- The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)