

# DIGITUS USB Type-C Adapter, USB A - USB-C

AK-300524-000-S  
EAN 4016032467410



## USB Type-C adapter, type A to C M/F, 3A, 5GB, 3.0 Version, bl

The DIGITUS® USB Type A to USB-C adapter allows you to use your current USB Type-C devices on an older USB A port. The adapter supports the USB 3.0 specification with data transfers of up to 5Gbps and provides a maximum power of 15 W (3 A). By simply flipping the USB-C connector, you can switch between USB 3.0 and USB 2.0 speeds if supported by the USB A connector. The integrated 56k pull-up resistor protects your devices from damage due to overload and supplies only as much power as the connected USB-C device needs. With this adapter you can use the full range of previous USB versions, backward compatible to the USB 2.0 / 1.1 standards.

### Connect USB-C devices to an USB A port - Keep using your devices with USB A port

- Adapter: From USB A to USB-C (Use USB-C devices on USB A ports)
- SuperSpeed data transfer: 5 Gbit/s (USB 3.0 if supported by USB A)
- Power supply USB-C: 3A max (15 W)
- USB Type-C plug: can be used on both sides, reverse polarity protected

- Integrated pull-up resistor 56k to protect your source devices (Notebook, PC)
- Abwärtskompatibel zu USB 2.0 / 1.1
- Operating temperature: -15 ~ 50°C
- Operating humidity: -25 ~ 80% RH (non-condensing)
- Storage temperature: -20 ~ 60°C
- Storage humidity: 20% - 85% RH (non-condensing)
- Material housing: aluminium
- Color: Black

### Attributes

- Color cable: black
- Connector 1: USB A, plug
- Connector 2: USB-C jack
- Connector surface: nickel-plated
- USB compliance: USB Type-C™
- USB-C Products: yes

### Package contents

- 1 x USB Type-C adapter, USB A - USB-C
- 1 x QIG

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	1000	9.00	35.00	26.00	24.00	21,840.00
Packaging Unit Inside	10	0.09	32.00	31.00	3.00	2,976.00
Packaging Unit Single	1	0.01	19.00	9.00	1.00	171.00
Net single without Packaging	1	0.01	0.60	1.40	3.80	0.00

**More images:**



**Safety notes**

- When plugging and unplugging the cable, only grasp the plug and do not pull directly on the cable.
- Cables must not be kinked sharply or bent at tight angles, as this can damage the inner wires and lead to failures.
- Make sure that the cables are not under tensile load, as this can damage the insulation and the wires inside the cable.
- Ensure that cables are not laid in areas where they can be easily damaged mechanically.
- Cables should not be used in environments with extremely high or very low temperatures. Observe the product information on the maximum operating temperature of the cable
- Check cables regularly for visible damage such as cracks, kinks or signs of wear. Defective cables should be replaced immediately to avoid failures, short circuits or even electric shocks.

**EU responsible person**

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH  
Auf dem Schüffel 3  
Lüdenscheid, Germany  
<https://www.assmann.com>  
[info@assmann.com](mailto:info@assmann.com)