DIGITUS Серийная интерфейсная плата, PCIe

DS-30000-1
EAN 4016032309390

Serial I/O RS232 PCIexpress Add-On card 2-port, incl. low profile, chipset:ASIX99100

Эту последовательную карту PCI Express Add-On Card вы можете вставить в ваш разъем PCI-Express и получить два последовательных порта RS232 (DB9). Основываясь на нативном однокристальном дизайне, он сокращает нагрузку на ЦП на вплоть до 48% по сравнению с обычными последовательными картами.

Идеально подходит для подключения серийных модемов, КПК, цифровых камер, принтеров, адаптеров ISDN и многих других устройств

- 2 шт. разъема DSUB 9, серийные интерфейсы, тип «папа», УАПП 16C950
- Чипсет: AX99100
- Скорость передачи данных до 1.5 Мбит / с
- Соответствует базовой спецификации PCI Express 2.0
- Совместим с управлением питания PCI 1.2
- Рабочая температура: 0-70 °C
- Влажность воздуха при эксплуатации: Относительная влажность 0% - 85% (без конденсации)
- Поддерживает Windows 10, 8.1, 8, 7, Vista, XP, Mac OS X и Linux

Package contents

- Серийная интерфейсная плата, PCIe
- Низкопрофильная планка
- Руководство по эксплуатации
- Драйвер CD

Logistics

	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	40	6.00	40.00	40.00	37.00	59,200.00
Packaging Unit Inside	1	0.15	6.00	18.00	18.00	1,944.00
Packaging Unit Single	1	0.15	6.00	18.00	18.00	1,944.00
Net single without Packaging	1	0.00	0.00	0.00	0.00	0.00

Safety notes

- Switch off the computer completely and disconnect it from the power supply before installing or removing the network card.
- Static discharge can damage the product or the PC. Take measures against static discharge (ESD) when installing the product, e.g. wear an antistatic wrist strap.
- Before installation, touch the metal surface of the PC housing or another grounded object to ground any ESD charge via the housing.
- Avoid using too much force when connecting the product to the PC.
- Please ensure that any cables are connected correctly without overstretching or damaging them.
- Avoid touching the contacts of the product with your fingers to prevent corrosion or static charge.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany

https://www.assmann.com
info@assmann.com