

# **DIGITUS Injetor de 16 portas 10G PoE+**

DN-95116 EAN 4016032430377





# Gigabit Ethernet PoE+ Injector Hub, 802.3at, 10G 16-port, Power Pins:3/6(+), 1/2(-), 250W

O DIGITUS® DN-95116 é um concentrador de 16 portas 10G PoE+ Midspan (injetor PoE). Este oferece 16 portas de entrada para dados e 16 portas de saída que disponibilizam dados e PoE. Cada porta PoE suporta equipamentos conectados em conformidade com o padrão PoE IEEE802.3af e IEEE802.3at com 15,4 watt ou 30 watt, como, p. ex., pontos de acesso PoE, telefone IP PoE ou câmaras IP PoE. O comutador disponibiliza para todas as portas uma força máxima de 250 watt e por porta uma força máxima de 30 watt.

## Redução dos custos de cablagens para equipamentos compatíveis com PoE

- 32 x 10/100/1000Mbps/2.5G/10G (16 x entrada de dados, 16 x saída de dados +PoE)
- Compatível com os padrões IEEE802.3af , IEEE802.3at
- Alimentação elétrica PoE via PIN 1,2(V-) e PIN 3,6(V+)
- Potência total máxima de 250 watt
- Compatível com os padrões IEEE802.3, IEEE802.3u, IEEE802.3ab

- Reconhecimento automático de cabo função auto MDI-/ MDI-X
- · Autorreconhecimento de full e half duplex
- Alimentação elétrica: 100VAC 240VAC
- Âmbito de temperatura de funcionamento: 0 °C a 40 °C
- Temperatura de armazenamento: -20°C 70°C
- Dimensões (mm): 440 (C) x 200 (L) x 45 (A)
- MTBF: 100.000 horas

#### **Attributes**

- Number of ports: 16
- PoE Power budget: 250 W
- PoE standard: IEEE802.3at (PoE+)
- Ethernet speed: 10 gigabit
- Industrial usage: no

#### **Package contents**

- Injetor de 16 portas 10G PoE+
- Peso: 20 g
- Cabo de rede
- Acessórios de montagem

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	5	20.83	59.50	29.50	22.00	38,615.50
Packaging Unit Inside	1	4.17	50.00	28.00	10.00	14,000.00
Packaging Unit Single	1	4.17	50.00	28.00	10.00	14,000.00
Net single without Packaging	1	2.80	44.00	20.00	4.50	0.00



### More images:



























### Safety notes

- This product is intended for indoor use only.
- Read all instructions and follow all warnings and instructions on the device.
- Do not place this appliance on an unstable surface (such as a trolley, stand, table, etc.).
- Do not use this appliance near water.
- Do not place this appliance near or above a radiator.
- The housing is equipped with openings for heat dissipation and ventilation. To prevent overheating during operation, the ventilation openings
  must not be blocked or covered.
- Do not place the appliance on a soft surface (e.g. bed, sofa, blanket, etc.). This will block the ventilation.
- The appliance must not be installed in a closed environment if adequate ventilation is not guaranteed.
- Do not spray any liquids onto the appliance.



- Disconnect the mains plug before cleaning. Do not use any liquid or foam cleaners.
- · Clean the appliance with a damp cloth.
- Connect the device according to the power supply on the rating plate.
- To prevent damage to the appliance, it is important that all appliances are properly earthed.
- Do not place any objects on the power cable and lay it in such a way as to avoid tripping hazards.
- · Use a surge protector, a regulator or an uninterruptible power supply (UPS) to protect your system from sudden, temporary and reduced power.
- Secure the system cable and mains cable properly and ensure that no objects are pressing on the cable.
- Do not insert any objects into the appliance through the openings in the housing. There is a risk of a short circuit, which can lead to fire or electric shock.
- Do not attempt to repair the appliance yourself. Always contact an authorized customer service centre.
- If any of the following conditions occur, unplug the appliance and return it to an authorized service centre for repair
- The mains cable, power supply unit or plug for the power supply is damaged or worn;
- · Liquid has penetrated the appliance;
- The device has been exposed to rain or water;
- The device has been dropped or the housing has been damaged;
- The function of the device has obviously changed;
- The appliance cannot be operated as described in the operating instructions.

#### EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH Auf dem Schüffel 3 Lüdenscheid, Germany https://www.assmann.com info@assmann.com