

DIGITUS® Mobile Desktop Charging Cabinet for 10 Notebooks/Tablets up to 13inch, UV-C, USB-C

DN-45004

EAN 4016032486145



Charging desktop cabinet, 13", USB-C, UV-C 10 charge bases, fan, 345 x 360 x 370 mm

The mobile charging cabinet from DIGITUS® is the ideal and compact solution for storing and charging your portable devices such as notebooks and tablets. Mobile charging cabinets are frequently used in public facilities such as schools in order to store devices securely at a central location while charging them at the same time. The cabinet includes 10 charging stations, all of which have their own USB connection on the front. Thanks to the integrated LED indicators, you have an overview of the charging process at all times (red: charging in progress; green: charging complete/no device connected). Wear-proof pedestals ensure slip-free construction. An installed ventilators combined with ventilation slits ensures active cooling of the cabinet. Installed UV-C lamps ensure sterile conditions and thus environmentally friendly, enhanced hygiene.

The ideal solution for sterile storage and charging your portable devices via USB-C™ connections.

- UV-C lamps for improved hygiene
- Steel front door with 3-point lock
- On/Off-switch on the side
- Power input: C19; 110V/220V AC, 50/60 Hz, 16A
- Power cable: 2 meter C19/safety plug
- Power output: 3500W
- 10 x USB-C™ connection

- Product dimensions (H x W x D) in mm: 345 x 360 x 370 mm
- Depth of inner tray: 294 mm
- Depth of inner shelf: 294 mm
- USB-C™ Port Output: 18W (5 V 3A/9V 2A/12V 1.5A) per port; 180W max.
- Temperature control: Fans start automatically when the internal temperature exceeds 40 °C

Attributes

- Color: black, RAL 9005
- Suitable for display size: 33 cm (13")
- Number of Devices: 10
- USB connection (charging): USB C
- Additional connection (charging): no
- UV-C disinfection: yes
- Data synchronisation function: no
- Type: Stationary
- Locking type: mechanical

Package contents

- 1 x Charging Cabinet
- 2 x Keys
- 1 x Power cable
- 1 x Manual

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	1	16.00	0.00	0.00	0.00	0.00
Packaging Unit Inside	1	16.00	0.00	0.00	0.00	0.00
Packaging Unit Single	1	16.00	0.00	0.00	0.00	0.00
Net single without Packaging	0	0.00	0.00	0.00	0.00	45.95

More images:



Safety notes

- The product may only be operated on sockets that are protected by a residual current circuit breaker.
- The electrical connection of the product must be made directly to a permanently installed socket.
- The use of multiple sockets or extension cables is not permitted.
- The connection cable must be undamaged. A cable with kinks, crushing or cracks must be replaced immediately.
- Before connecting electrical devices to the product, ensure that the device to be connected, including its connection cable, is in a fault-free and damage-free condition.
- Always insert the plug fully into the socket. It may only be disconnected by pulling on the plug itself - never pull on the cable.
- When operating doors or flaps, care must be taken to ensure that the connecting cables of electrical devices are not crushed or damaged
- Use only in dust and moisture-protected indoor areas
- Prevent higher humidity or temperatures than those specified in the data sheet - Avoid moisture, dust or vapors, solvents, flammable gases.
- Avoid moisture, dust or vapors, solvents, flammable gases.
- The appliance may only be dismantled and transported if the mains plug has been disconnected beforehand.
- Only connect the charging system to an earthed and easily accessible socket.
- Safety must be assessed by a qualified electrician.
- The sockets may only be used with the devices intended for this purpose, for example:
 - Chargers for rechargeable batteries and hand-held devices
 - Smartphones or tablets (mobile devices)
 - Laptops / Notebooks / UltraBooks (mobile computers)
 - Mobile batteries / PowerBanks
- Please ensure that the maximum total output specified on the rating plate is not exceeded.
- Please also ensure that no liquids enter the electrical equipment of the cabinet.
- Only charge devices under supervision. Long-term storage of any devices with Li-ion batteries is not permitted.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
 Auf dem Schüffel 3
 Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com